



DIGISTART 340 PULSE-TRONIC 230V 12-24V



Overview

DIGISTART 340 PULSE-TRONIC 230V 12-24V

cod. 829327

Digital battery charger and starter with electronic control of the charging current, automatic interruption and restart (PULSE-TRONIC) for charging all types of maintenance free, sealed batteries (GEL/AGM/START-STOP), free electrolyte batteries (WET) with 12/24V voltages and quick starting of cars, vans and light trucks.

Features:

- microprocessor control
- display to check charging current, voltage and battery charging level
- choice of TEST, CHARGE, TRONIC mode
- CHARGE function: constant current charge as set on the front panel - choice of output voltage, type of charge, charging mode
- protection against overloads and polarity reversal.



1 PH 230V



BOAT



CE MARKING



MICROPROCESSOR



TRACTOR



EAC CERTIFICATION



CAR



VAN

Technical data



CODE 829327



CURRENT RANGE 1 - 30 A



MAX RATED REFERENCE CAPACITY
450 Ah



SINGLE PHASE MAINS VOLTAGE 230 V



EFFECTIVE CHARGING CURRENT 45 A



DIMENSIONS 30,5 - 36 - 63 cm



DIGISTART 340 PULSE-TRONIC 230V 12-24V

MAINS FREQUENCY 50 - 60 Hz	RATED CHARGE CURR. EN60335-2-29 30 A	WEIGHT 13,8 kg
CHARGE POWER 1 KW	START CURRENT 1V/C EN60335-2-29 180 A	EAN CODE 800489773281 7
START POWER 6,4 KW	MAX STARTING CURRENT 300 A	PIECES/PALLET 18 pz/pallet
CHARGING VOLTAGE 12 / 24 V	MIN. RATED REFERENCE CAPACITY 10 Ah	

Included Accessories

COLORADO 150B WORK CLAMP 150A - 712001	COLORADO 150R POSITIVE CLAMP 150A - 712002
--	--